RAB Design

LL32 WITH SPIKE AND RECEPTACLE

The LL series of pagoda garden fixtures have a classic look and are designed to withstand the Canadian environment. All LL series are cast units. The LL32 is ideal for daisy chaining together with its 8' cord with a grounded plug on one side and a receptacle on the other side. The LL32 has a 6" top and 3 lower tiers with a clear glass globe. Maximum wattage 100 incandescent.

TIERS Precision die cast with a powder coat paint finish.

BOTTOM FITTER Precision die cast with internal threads for holding glass globe. Bottom of fitter is threaded for 1/2" NPS pipe. Tiers are mounted to bottom fitter with stainless set screws.Bottom fitter has a powder coat paint finish.

GLASS Clear glass with threading. Replacement glass is GL100.

SOCKET Medium base 4KV pulse-rated socket with a nickle-plated screw shell and a spring-loaded centre contact.

ELECTRICAL RECEPTACLE Precision die cast with a grounded receptacle on one side with cover and an 8' cord on the other side with a grounded plug. Cord is rated for outdoor use. Electrical receptacle has a powder coat paint finish.



SPIKE Precision die cast with a powder coat paint finish.

HARDWARE All external hardware is stainless steel.

FINISH Standard finishes are black and green. Custom colours are available, please consult factory.

LAMP Lamp not included.



www.rabdesign.ca

